



- 1) Button
- 2) Fixing part
- 3) Lighting tunnel
- 4) Frame
- 5) Base
- 6) Screw of the claw
- 7) Tumbler

Technical Features:

- Single- pole, single- way, instant push button, 10A 250V~ switch
- 5 mA blue light and a life- span of 100.000 hours (~11 years). (LEDs)
- LEDs that can operate when external phase connection to the switch is made.

Assembly:

- 1- The cable connections should be done as shown in the connection diagram.
- L2 external phase connection should be done in order for the LEDs to light up.

2- Place the base (5) in the mounting box and tighten the screws of the claws (6) with an appropriate screwdriver.

3- Place the fixing part (2) to the frame (4). Lighting tunnels (3) should be put in the slot on the side of the frame.

4- Put the frame on the base and fix the frame to the base by pressing on the lighting tunnels as shown in the figure (8).

5-The assembly is completed after the pins inside the button (1) are pushed into the slots on the tumbler (7).